



## PERFORM 4500 C5

PORTABLE POWER

GENERATING SET Range PERFORM

### PRODUCT ADVANTAGES

- Compact frame with protection panels against shocks
- Starting up facilitated thanks to the summer/winter positions
- KOHLER air-cooled industrial engine
- Good value for money
- Generating set guaranteed 3 years

**QUAD CLEAN AIR FILTER** The Cyclonic Quad Clean air filters provide 4 levels of filtration which effectively filter out large particles and capture the finest particles. They ensure a continuous supply of clean air to the engine, fuel economies, increase the engine performance and extend its lifetime  
**STAGE V (2016/1628 EU)** : This product is compliant with regulation for implementing requirements relating to gaseous and pollutant emission limits in Europe

### Range PERFORM

An efficient, cost effective and easy to handle equipment, suitable for frequent use.



This product meets the Qualigen charter, which aims to ensure a high level of quality and guarantee the safety of users. Qualigen: commitment to safety and quality.

## PERFORM 4500 C5

### GENERAL SPECIFICATIONS

Range	PERFORM
Frequency (Hz)	50 Hz
Max power (kW) *	4
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	7.30
75% cons. (l/h) *	1.70
75% Autonomy (h) *	4.30
Sound power level guaranteed LwA dB(A)	96
Acoustic pressure level @1m in dB(A)	83
Acoustic pressure level @7m in dB(A)	68

### ENGINE SPECIFICATIONS

Engine brand	KOHLER
Engine type	CH395_C5
Engine Type	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm3)	277
Oil system capacity including filters (l)	1.10

### ALTERNATOR SPECIFICATIONS

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

### PLUGS AND PANEL DESCRIPTIVE

2 230V 10/16A sockets - circuit breaker

### DIMENSIONS AND WEIGHT

Length (cm)	71
Width (cm)	55.50
Height (cm)	49
Dry Weight (kg)	61.50

### PACKAGING

Packaging type	Box
Length (cm)	73
Width (cm)	58
Height (cm)	49.50
Weight (kg)	63.50
Pallet type	120/80
Number of box by pallet	6
Pallet height (cm)	162
weight of the packaged Pallet (kg)	391

### ACCESSORIES SUPPLIED



Funnel
Floor maintaining slot



User and maintenance manual
Ergonomic handle grip

### OPTIONS



<b>R01</b>	This set includes the hour meter and the differential circuit breaker.
------------	--



<b>R05M</b>	The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut.
-------------	---



<b>RKB1HD</b>	Trolley kit for the generating sets of 6kW or below
---------------	---



<b>RKS2</b>	Maintenance kit for KOHLER CH395 and CH440 engines.
-------------	---



<b>RH1</b>	Cover for SDMO's generating sets, welding sets and water pumps
------------	--



<b>RPM</b>	Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V
------------	---



<b>RPQ</b>	For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm² cable.
------------	--



<b>RKD1</b>	kit of two diferential removable adapters for domestic sockets. Schema for ground bonding with isolated neutral
-------------	---